

## Digital Output Module DOM4-8



**Part-No. 583361.22**

Part of EN 54-16 approval

### Features:

- Compliant with EN 60849 and EN 50849
- EN 54-16 certified
- 16 audio slots giving a total of 1 hour memory
- 4 independent amplifier channels suitable for use with spurs, zones or loop technology. Built in parametric equalizer, compressor limiter and delay function (upto 9.9 seconds)
- All functions of an alarm and evacuation system
- Network into a large system via Ethernet connection
- Offers full monitoring of the system functions
- Automatic and dynamic switching to redundant emergency amplifiers
- Automatic volume control (AVC) even during announcements
- Remote monitoring and configuration via the network
- 24 V DC emergency power supply

The DOM (Digital Output Module) is the central control element of VARIODYN D1. It has interfaces to all input/output assemblies, administers, and monitors the loudspeaker circuits for voice alarm systems and electro-acoustic emergency warning system per EN 60849 and EN 50849. Large or complex system configurations can be implemented through the networking of multiple DOMs via Ethernet. The DOM offers a high level of automatic and constant monitoring as standard. All connected power amplifiers are permanently monitored by the DOM and if a power amplifier becomes faulty, it can be replaced dynamically by a backup amplifier or a backup amplifier channel. The switchover is done automatically by the DOM. The loudspeaker lines are permanently monitored for short circuit, ground fault, and failure as well as impedance deviation. Faulty loudspeaker zones are separated in a non-reacting manner. A DOM contains storage capacity for preset announcements, which can be used for alarm texts and signals (escape alarm, caution signal) and warning signals (gongs). The volume of each source and each amplifier channel can be controlled. Additional filters like parametric equalizer, high-and low pass filter are available. All errors are recognized, displayed and recorded within few seconds meeting the standards. For special applications such as e.g. tunnel, a delay in all four channels can be programmed up to 9.9 sec.

With the new Firmware it is now possible to connect up to 400 units and get advantage of the new logical functions which makes it much easier and efficient to configure the DOM.

The control unit DOM4-8 is equipped with 4 independent amplifier channels in order to operate 8 loudspeaker areas or 4 loudspeaker circuits in VARIODYN D1 loop technology. There is also the option of mixing loop and spur technology with a DOM.

Rated voltage	90 .. 264 V AC
Rated frequency	47 ... 63 Hz
Power consumption	40 / 70 W
Contact load relay	100 V DC/1 A
Ambient temperature	-5 °C ... 55 °C
Air humidity	15 ... 90 % (non-condensing)
Weight	approx. 5.7 kg
Dimensions	W: 483 mm H: 44 mm D: 345 mm (1 HU, 19")

### Accessories:

- 583451.21 Cable for cabinet rear panel DOM4-8
- 583486 Patch cable CAT5, 1 m yellow (Ethernet)
- 583487 Patch cable CAT5, 2 m yellow (Ethernet)
- 583488 Patch cable CAT5, 3 m yellow (Ethernet)
- 583496 End-of-line module (EOL)
- 581310 Measuring microphone for D1 AVC in a 5" recessed ceiling housing
- 581316 Microphone, for AVC
- 583703 Mounting set 1
- 583342 Loop Isolator Module
- 583708.HO Ventilation panel 1 HU with Honeywell logo